

Braemar product codes

			Codes	Example
Family				
Braemar			BR2	BR2
Light Engine				
Performance LED				16
8 LED			8	
16 LED			16	
24 LED			24	
	Performance CoB			
	Single CoB		PC	
		Comfort CoB		
		Single CoB	CC	
Colour Temperature				
2200K	2200K	2200K	22	30
2700K	2700K	2700K	27	
3000K	3000K	3000K	30	
4000K	4000K	-	40	
-	Tunable White 1800-4000K	Tunable White 1800-3000K	TW	
Distribution				
Roads - Diamond+ A Optic			A1 / A2 / A3 / A5 / A6	A1
Pathways - Diamond+ B Optic			B1 / B2 / B3	
Areas - Diamond+ C Optic			C1 / C2 / C6	
Crossings - Diamond+ Z Optic			ZR / ZL / ZF	
	Roads - AC1		AC1	
	Pathways - BC1		BC1	
	Areas - CC1		CC1	
	Roads - DC1		DC1	
		Symmetric	SY	
Light Shield (optional)				
Light shield – internal 150° short (200mm)			L1	-
Light shield – internal 150° full			L2	
Light shield – internal 180° full			L3	
Drive Current				
Drive currents from 250mA to 1050mA are available in 50mA increments Insert drive current value (e.g. 700mA = 700)			250 / 300 / 350 / 400 / 450 / 500 / 550 / 600 / 650 / 700 / 750 / 800 / 850 / 900 / 950 / 1000 / 1050	700
Notes 24 LED = 850mA maximum				
Product Colours				
RAL 9005 Black			10	10
RAL 6005 Light moss green			50	
RAL 3005 Wine red			70	
RAL 5003 Sapphire blue			30	
RAL 7037 Dusty grey			21	
RAL 7016 Anthracite grey			20	
Other colours available on request			RAL [specify]	
Paint Finish				
Polyester powder coat			PP	PP
Marine-grade coating			MG	
Control				
No control			N	35L
Miniature Photocell 20 lux (1:1)			20L	
Miniature Photocell 35 lux (1:0.5)			35L	
4-pin Zhaga Book 18 socket (top)			Z4	
Integral CMS - Urban Control (AC node with puck antenna)			UAC	
Integral CMS - Urban Control (DC node with puck antenna)			UDC	
Integral CMS - Telensa (with monopole antenna)			ITE	
Integral CMS - Mayflower (with stub antenna)			IMA	
Internal Wiring				
3-core [default option]			3	3
5-core			5	
Example code = BR2 16 30 A1 700 10 PP 35L 3				

For further help specifying a product, please [contact us](#)